

## Cable Calculations

Project Name Proposed Residential Development at Boherboy REV D  
Project Number 21058

Midi Pillar Number 1							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	5	0.55	211	0.30	0.85	0.37%
2	7.3	10	0.75	336		1.84	0.80%
Circuit	$Z_E$	Conductor Resistance $\Omega/\text{km}$	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.30	1.6	139.4	10	6mm <sup>2</sup>
2	0.35	3.08	2.07	2.4	95.1	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

The voltage drop on each circuit is below the allowed maximum.  
The minimum sized cable permissible under I.S. 10101:2020 is 6mm SQ.  
It is the duty of the electrical contractor to calculate the appropriate fuse size.

Approximate Total Cable (m) = 8755

Midi Pillar Number 2							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	8	0.30	260	0.18	0.57	0.25%
2	7.3	4	0.18	124		0.16	0.07%
3	7.3	5	0.30	155		0.34	0.15%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.60	2.0	117.9	10	6mm <sup>2</sup>
2	0.35	3.08	0.76	1.1	206.5	10	6mm <sup>2</sup>
3	0.35	3.08	0.95	1.3	176.3	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 3							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	5	0.30	189	0.25	0.41	0.18%
2	7.3	7	0.43	297		0.93	0.41%
3	7.3	5	0.35	174		0.44	0.19%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.16	1.5	151.9	10	6mm <sup>2</sup>
2	0.35	3.08	1.83	2.2	105.5	10	6mm <sup>2</sup>
3	0.35	3.08	1.07	1.4	161.8	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 4							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	2	0.13	82	0.21	0.08	0.03%
2	7.3	4	0.24	171		0.30	0.13%
3	7.3	9	0.56	300		1.23	0.53%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.51	0.9	269.0	10	6mm <sup>2</sup>
2	0.35	3.08	1.05	1.4	163.9	10	6mm <sup>2</sup>
3	0.35	3.08	1.85	2.2	104.6	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 5							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	10	0.54	338	0.31	1.33	0.58%
2	7.3	5	0.33	196		0.47	0.21%
3	7.3	10	0.46	299		1.00	0.44%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	2.08	2.4	94.6	10	6mm <sup>2</sup>
2	0.35	3.08	1.21	1.6	147.7	10	6mm <sup>2</sup>
3	0.35	3.08	1.84	2.2	104.9	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 6							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	4	0.18	139	0.23	0.18	0.08%
2	7.3	7	0.43	198		0.62	0.27%
3	7.3	6	0.39	226		0.64	0.28%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.86	1.2	190.7	10	6mm <sup>2</sup>
2	0.35	3.08	1.22	1.6	146.5	10	6mm <sup>2</sup>
3	0.35	3.08	1.39	1.7	132.0	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 7							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	5	0.37	147	0.25	0.40	0.17%
2	7.3	7	0.40	251		0.73	0.32%
3	7.3	7	0.30	243		0.53	0.23%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.91	1.3	183.2	10	6mm <sup>2</sup>
2	0.35	3.08	1.55	1.9	121.3	10	6mm <sup>2</sup>
3	0.35	3.08	1.50	1.8	124.5	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 8							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	6	0.36	210	0.21	0.55	0.24%
2	7.3	6	0.33	178		0.43	0.19%
3	7.3	4	0.23	161		0.27	0.12%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_s$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.29	1.6	139.9	10	6mm <sup>2</sup>
2	0.35	3.08	1.10	1.4	159.0	10	6mm <sup>2</sup>
3	0.35	3.08	0.99	1.3	171.4	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 9							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	3	0.33	109	0.33	0.26	0.11%
2	7.3	9	0.44	333		1.07	0.47%
3	7.3	9	0.66	333		1.60	0.70%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_s$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.67	1.0	225.2	10	6mm <sup>2</sup>
2	0.35	3.08	2.05	2.4	95.8	10	6mm <sup>2</sup>
3	0.35	3.08	2.05	2.4	95.8	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 10							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	7	0.39	226	0.21	0.64	0.28%
2	7.3	3	0.18	92		0.12	0.05%
3	7.3	5	0.35	174		0.44	0.19%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.39	1.7	132.0	10	6mm <sup>2</sup>
2	0.35	3.08	0.57	0.9	250.9	10	6mm <sup>2</sup>
3	0.35	3.08	1.07	1.4	161.8	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 11							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	8	0.48	272	0.19	0.95	0.41%
2	7.3	9	0.36	342		0.90	0.39%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.68	2.0	113.6	10	6mm <sup>2</sup>
2	0.35	3.08	2.11	2.5	93.6	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 12							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	6	0.31	172	0.14	0.39	0.17%
2	7.3	3	0.12	102		0.09	0.04%
3	7.3	3	0.19	102		0.14	0.06%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.06	1.4	163.2	10	6mm <sup>2</sup>
2	0.35	3.08	0.63	1.0	235.1	10	6mm <sup>2</sup>
3	0.35	3.08	0.63	1.0	235.1	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 13							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	5	0.32	177	0.17	0.41	0.18%
2	7.3	4	0.16	172		0.20	0.09%
3	7.3	4	0.25	102		0.19	0.08%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.09	1.4	159.7	10	6mm <sup>2</sup>
2	0.35	3.08	1.06	1.4	163.2	10	6mm <sup>2</sup>
3	0.35	3.08	0.63	1.0	235.1	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 14							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	3	0.18	103	0.24	0.14	0.06%
2	7.3	6	0.48	265		0.93	0.40%
3	7.3	5	0.37	164		0.44	0.19%
Circuit	$Z_E$	Conductor Resistance $\Omega/\text{km}$	$Z_s$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.63	1.0	233.6	10	6mm <sup>2</sup>
2	0.35	3.08	1.63	2.0	116.0	10	6mm <sup>2</sup>
3	0.35	3.08	1.01	1.4	169.1	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Midi Pillar Number 15							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	8	0.37	254	0.18	0.69	0.30%
2	7.3	1	0.07	36		0.02	0.01%
3	7.3	5	0.35	174		0.44	0.19%
Circuit	$Z_E$	Conductor Resistance $\Omega/\text{km}$	$Z_s$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	1.56	1.9	120.1	10	6mm <sup>2</sup>
2	0.35	3.08	0.22	0.6	402.3	10	6mm <sup>2</sup>
3	0.35	3.08	1.07	1.4	161.8	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*



Midi Pillar Number 16							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	3	0.12	102	0.12	0.09	0.04%
2	7.3	8	0.32	297		0.69	0.30%
3	7.3	2	0.08	86		0.05	0.02%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.63	1.0	235.1	10	6mm <sup>2</sup>
2	0.35	3.08	1.83	2.2	105.5	10	6mm <sup>2</sup>
3	0.35	3.08	0.53	0.9	261.4	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

Landlord Midi Pillar Number 17							
Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	1	0.04	32	0.04	0.01	0.00%
2	7.3	1	0.06	31		0.01	0.01%
3	7.3	2	0.08	38		0.02	0.01%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.20	0.5	420.4	10	6mm <sup>2</sup>
2	0.35	3.08	0.19	0.5	425.2	10	6mm <sup>2</sup>
3	0.35	3.08	0.23	0.6	393.8	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

### Landlord Midi Pillar Number 18

Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	1	0.06	16	0.03	0.01	0.00%
2	7.3	2	0.08	85		0.05	0.02%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.10	0.4	512.8	10	6mm <sup>2</sup>
2	0.35	3.08	0.52	0.9	263.3	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

### Landlord Midi Pillar Number 19

Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	1	0.04	18	0.03	0.01	0.00%
2	7.3	2	0.08	55		0.03	0.01%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.11	0.5	499.0	10	6mm <sup>2</sup>
2	0.35	3.08	0.34	0.7	333.9	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

### Landlord Midi Pillar Number 20

Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	1	0.04	34	0.04	0.01	0.00%
2	7.3	1	0.04	15		0.00	0.00%
3	7.3	2	0.08	59		0.03	0.01%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.21	0.6	411.1	10	6mm <sup>2</sup>
2	0.35	3.08	0.09	0.4	519.9	10	6mm <sup>2</sup>
3	0.35	3.08	0.36	0.7	322.4	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

### Landlord Midi Pillar Number 21

Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	2	0.08	41	0.02	0.02	0.01%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.25	0.6	381.7	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

### Landlord Midi Pillar Number 22

Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	2	0.08	35	0.02	0.02	0.01%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.22	0.6	406.6	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*

### Landlord Midi Pillar Number 23

Circuit	Tabulated Voltage drop (cable)	Total columns on circuit	Total luminaire Current ( $I_D$ )	Total circuit length	kVA for pillar	Voltage drop	Voltage drop percentage
1	7.3	1	0.04	15	0.01	0.00	0.00%
Circuit	$Z_E$	Conductor Resistance $\Omega$ /km	$Z_S$	Circuit Impedance Ohm	Fault Current Amp	Circuit Fuse ( $I_N$ ) Amp	Cable size
1	0.35	3.08	0.09	0.4	519.9	10	6mm <sup>2</sup>

*Note that circuit length includes an extra 10m per column to allow for turns, access and other potential issues.  
It is the duty of the electrical contractor to undertake appropriate electrical safety tests and to certify the electrical installation.*